EPC2202 - Automotive 80 V (D-S) Enhancement Mode Power Transistor

V_{DS} , 80 V
$R_{DS(on)}$, 17 mΩ
I_D , 18 A
AEC-Q101



EFFICIENT POWER CONVERSION

RoHS Halogen-Free

Revised April 25, 2025

Gallium Nitride's exceptionally high electron mobility and low temperature coefficient allows very low $R_{DS(on)}$, while its lateral device structure and majority carrier diode provide exceptionally low Q_G and zero Q_{RR}. The end result is a device that can handle tasks where very high switching frequency, and low on-time are beneficial as well as those where on-state losses dominate.

Application Notes:

- Easy-to-use and reliable gate, Gate Drive ON = 5–5.25 V typical, OFF = 0 V (negative voltage not needed)
- Top of FET is electrically connected to source

Questions: Ask a GaN Expert



Die size: 2.1 x 1.6 mm

EPC2202 eGaN® FETs are supplied only in passivated die form with solder bars.

Applications

- Lidar/pulsed power applications
- High power density DC-DC converters
- Class-D audio
- High intensity headlamps

Benefits

- Ultra high efficiency
- Ultra low $R_{DS(on)}$
- Ultra low Q_G
- Ultra small footprint

Maximum Ratings			
PARAMETER		VALUE	UNIT
V_{DS}	Drain-to-Source Voltage (Continuous)	80	V
I_D	Continuous (T_A = 25°C, $R_{\theta JA}$ = 12°C/W)	18	A
	Pulsed (25°C, T_{PULSE} = 300 µs)	75	
V_{GS}	Gate-to-Source Voltage	5.75	V
	Gate-to-Source Voltage	-4	
T_J	Operating Temperature	–55 to 150	°C
T_{STG}	Storage Temperature	–55 to 150	

Thermal Characteristics			
PARAMETER		TYP	UNIT
$R_{\theta JC}$	Thermal Resistance, Junction-to-Case	2	°C/W
$R_{\theta JB}$	Thermal Resistance, Junction-to-Board	4	
$R_{\theta JA}$	Thermal Resistance, Junction-to-Ambient (Note 1)	69	

Note 1: $R_{\theta JA}$ is determined with the device mounted on one square inch of copper pad, single layer 2 oz copper on FR4 board. See https://epc-co.com/epc/documents/product-training/Appnote_Thermal_Performance_of_eGaN_FETs.pdf for details.

Static Characteristics (T_J = 25°C unless otherwise stated)						
PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
BV_{DSS}	Drain-to-Source Voltage	V_{GS} = 0 V, I_D = 300 µA	80			V
I_{DSS}	Drain-Source Leakage	V_{DS} = 64 V, V_{GS} = 0 V		20	250	µA
I_{GSS}	Gate-to-Source Forward Leakage	V_{GS} = 5 V		0.01	3	mA
	Gate-to-Source Reverse Leakage	V_{GS} = -4 V		0.01	0.25	mA
$V_{GS(TH)}$	Gate Threshold Voltage	V_{DS} = V_{GS}, I_D = 3 mA	0.8	1.4	2.5	V
$R_{DS(on)}$	Drain-Source On Resistance	V_{GS} = 5 V, I_D = 11 A		12	17	mΩ
V_{SD}	Source-Drain Forward Voltage	I_S = 0.5 A, V_{GS} = 0 V		1.8		V

All measurements were done with substrate connected to source.

Dynamic Characteristics# (T_J = 25°C unless otherwise stated)						
PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
C_{ISS}	Input Capacitance	V_{DS} = 50 V, V_{GS} = 0 V		345	415	pF
C_{RSS}	Reverse Transfer Capacitance			3		
C_{OSS}	Output Capacitance			230	345	
$C_{OSS(ER)}$	Effective Output Capacitance, Energy Related (Note 2)	V_{DS} = 0 to 50 V, V_{GS} = 0 V		279		
$C_{OSS(TR)}$	Effective Output Capacitance, Time Related (Note 3)			352		
R_G	Gate Resistance			0.4		Ω
Q_G	Total Gate Charge	V_{DS} = 50 V, V_{GS} = 5 V, I_D = 11 A		3.2	4	nC
Q_{GS}	Gate-to-Source Charge	V_{DS} = 50 V, I_D = 11 A		1		
Q_{GD}	Gate-to-Drain Charge			0.55		
$Q_{G(TH)}$	Gate Charge at Threshold			0.7		
Q_{OSS}	Output Charge	V_{DS} = 50 V, V_{GS} = 0 V		18	27	
Q_{RR}	Source-Drain Recovery Charge			0		

Defined by design. Not subject to production test.
All measurements were done with substrate connected to source.
Note 2: $C_{OSS(ER)}$ is a fixed capacitance that gives the same stored energy as C_{OSS} while V_{DS} is rising from 0 to 62.5% BV_{DSS}.
Note 3: $C_{OSS(TR)}$ is a fixed capacitance that gives the same charging time as C_{OSS} while V_{DS} is rising from 0 to 62.5% BV_{DSS}.

Figure 1: Typical Output Characteristics at 25°C



Figure 2: Typical Transfer Characteristics



Figure 3: $R_{DS(on)}$ vs. V_{GS} for Various Currents



Figure 4: $R_{DS(on)}$ vs. V_{GS} for Various Temperatures



Figure 5a: Typical Capacitance (Linear Scale)



Figure 5b: Typical Capacitance (Log Scale)



Figure 5c: Typical Output Charge and C_{OSS} Stored Energy



Figure 6: Typical Gate Charge



Figure 7: Typical Reverse Drain-Source Characteristics



Figure 8: Normalized On-State Resistance vs. Temperature



Note: Negative gate drive voltage increases the reverse drain-source voltage. EPC recommends 0 V for OFF.

Figure 9: Normalized Threshold Voltage vs. Temperature



Figure 10: Transient Thermal Response Curves



Figure 11: Safe Operating Area



TAPE AND REEL CONFIGURATION

4mm pitch, 8mm wide tape on 7" reel



	Dimension (mm)		
EPC2202 (Note 1)	Target	MIN	MAX
a	8.00	7.90	7.30
b	1.75	1.65	1.85
c (Note 2)	3.50	3.45	3.55
d	4.00	3.90	4.10
e	4.00	3.90	4.10
f (Note 2)	2.00	1.95	2.05
g	1.50	1.50	1.60

Note 1: MSL 1 (moisture sensitivity level 1) classified according to IPC/JEDEC industry standard.

Note 2: Pocket position is relative to the sprocket hole measured as true position of the pocket, not the pocket hole.

DIE MARKINGS



Part Number	Laser Markings		
	Part # Marking Line 1	Lot_Date Code Marking Line 2	Lot_Date Code Marking Line 3
EPC2202	2202	YYYY	ZZZZ

DIE OUTLINE

Solder Bar View



Side View



DIM	MICROMETERS		
	MIN	Nominal	MAX
A	2076	2106	2136
B	1602	1632	1662
c	1379	1382	1385
d	577	580	583
e	235	250	265
f	195	200	205
g	400	400	400

Pad no. 1 is Gate;
Pads no. 3, 5 are Drain;
Pads no. 4, 6 are Source;
Pad no. 2 is Substrate.*

*Substrate pin should be connected to Source

RECOMMENDED LAND PATTERN

(units in µm)



The land pattern is solder mask defined.

Pad no. 1 is Gate;
Pads no. 3, 5 are Drain;
Pads no. 4, 6 are Source;
Pad no. 2 is Substrate. *

*Substrate pin should be connected to Source

Solder mask
(for solder mask defined pads)

RECOMMENDED STENCIL DRAWING

(measurements in µm)



Recommended stencil should be 4mil (100 µm) thick, must be laser cut, opening per drawing.
The corner has a radius of R60

Intended for use with SAC305 Type 4 solder, reference 88.5% metals content.

Additional assembly resources available at

TYPICAL THERMAL CONCEPT

The EPC2202 can take advantage of dual sided cooling to maximize its heat dissipation capabilities in high power density designs.

Recommended best practice thermal solutions are covered in detail in **How2AppNote012 - How to Get More Power Out of an eGaN Converter.pdf**.



Figure 13: Exploded view of heatsink assembly using screws



Figure 14: A cross-section image of dual sided thermal solution

Note: Connecting the heatsink to ground is recommended and can significantly improve radiated EMI

The thermal design can be optimized by using the ***GaN FET Thermal Calculator*** on EPC's website.

Solder mask defined pads are recommended for best reliability.



Figure 15: Solder mask defined versus non-solder mask defined pad



Figure 16: Effect of solder mask design on the solder ball symmetry

- Assembly resources – https://epc-co.com/epc/Portals/0/epc/documents/product-training/Appnote_GaNassembly.pdf
- Library of Altium footprints for production FETs and ICs – https://epc-co.com/epc/documents/altium-files/EPC%20Altium%20Library.zip (for preliminary device Altium footprints, contact EPC)

Efficient Power Conversion Corporation (EPC) reserves the right to make changes without further notice to any products herein to improve reliability, function or design. EPC does not assume any liability arising out of the application or use of any product or circuit described herein; neither does it convey any license under its patent rights, nor the rights of others.

eGaN® is a registered trademark of Efficient Power Conversion Corporation.
EPC Patent Listing https://epc-co.com/epc/about-epc/patents

Information subject to change without notice.

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.