Linear Regulator – Dual-Rail, Very Low-Dropout, Programmable Soft-Start

3.0 A

NCV59749

The NCV59749 is dual−rail very low dropout voltage regulator that is capable of providing an output current in excess of 3.0 A with a dropout voltage of 120 mV typ. at full load current. The devices are stable with ceramic and any other type of output capacitor ≥ 2.2 μF. This series contains adjustable output voltage version with output voltage down to 0.8 V. Internal protection features consist of built−in thermal shutdown and output current limiting protection. User−programmable Soft−Start and Power Good pins are available. The NCV59749 is available in QFN20 5x5 package.

Features

- Output Current in Excess of 3.0 A
- V_{IN} Range: 0.8 V to 5.5 V
- V_{BIAS} Range: 2.7 V to 5.5 V
- Output Voltage Range: 0.8 V to 3.6 V
- Dropout Voltage: 120 mV at 3 A
- Programmable Soft Start
- Open Drain Power Good Output
- Fast Transient Response
- Stable with Any Type of Output Capacitor ≥ 2.2 μF
- Current Limit and Thermal Shutdown Protection
- NCV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC−Q100 Qualified and PPAP Capable
- These are Pb−Free Devices

Applications

- Automotive, Consumer and Industrial Equipment Point of Load Regulation
- FPGA, DSP and Logic Power Supplies
- Switching Power Supply Post Regulation



Figure 1. Typical Application Schematic



QFN20
CASE 485DB

MARKING DIAGRAM



QFN20

A	= Assembly Location
WL	= Wafer Lot
YY	= Year
WW	= Work Week
▪	= Pb-Free Package

(Note: Microdot may be in either location)

PIN CONNECTIONS



QFN20, 5x5, 0.65P

ORDERING INFORMATION

See detailed ordering, marking and shipping information in the package dimensions section on page 9 of this data sheet.

© Semiconductor Components Industries, LLC, 2017



Figure 2. Simplified Schematic Block Diagram

Table 1. PIN FUNCTION DESCRIPTION

Name	QFN20	Description
IN	5–8	Unregulated input to the device.
EN	11	Enable pin. Driving this pin high enables the regulator. Driving this pin low puts the regulator into shutdown mode. This pin must not be left floating.
SS	15	Soft-Start pin. A capacitor connected on this pin to ground sets the start-up time. If this pin is left floating, the regulator output soft-start ramp time is typically 200 μs.
BIAS	10	Bias input voltage for error amplifier, reference, and internal control circuits.
PG	9	Power-Good (PG) is an open-drain, active-high output that indicates the status of V_{OUT}. When V_{OUT} exceeds the PG trip threshold, the PG pin goes into a high-impedance state. When V_{OUT} is below this threshold the pin is driven to a low-impedance state. A pull-up resistor from 10 kΩ to 1 MΩ should be connected from this pin to a supply up to 5.5 V. The supply can be higher than the input voltage. Alternatively, the PG pin can be left floating if output monitoring is not necessary.
FB	16	This pin is the feedback connection to the center tap of an external resistor divider network that sets the output voltage. This pin must not be left floating.
OUT	1, 18–20	Regulated output voltage. A small capacitor (total typical capacitance ≥ 2.2 μF, ceramic) is needed from this pin to ground to assure stability.
NC	2–4, 13, 14, 17	No connection. This pin can be left floating or connected to GND to allow better thermal contact to the top-side plane.
GND	12	Ground
PAD/TAB		Should be soldered to the ground plane for increased thermal performance

Share Feedback
Your Opinion Matters

Table 2. ABSOLUTE MAXIMUM RATINGS

Symbol	Parameter	Value	Unit
V_{IN}	Input Voltage Range	−0.3 to +6	V
V_{BIAS}	Input Voltage Range	−0.3 to +6	V
V_{EN}	Enable Voltage Range	−0.3 to +6	V
V_{PG}	Power-Good Voltage Range	−0.3 to +6	V
I_{PG}	PG Sink Current	0 to +1.5	mA
V_{SS}	SS Pin Voltage Range	−0.3 to +6	V
V_{FB}	Feedback Pin Voltage Range	−0.3 to +6	V
V_{OUT}	Output Voltage Range	−0.3 to (V_{IN} + 0.3) ≤ 6	V
I_{OUT}	Maximum Output Current	Internally Limited	
	Output Short Circuit Duration	Indefinite	
P_D	Continuous Total Power Dissipation	See Thermal Characteristics Table and Formula	
T_{JMAX}	Maximum Junction Temperature	+125	°C
T_{STG}	Storage Junction Temperature Range	−55 to +150	°C
ESD_{HBM}	ESD Capability, Human Body Model (Note 2)	2000	V
ESD_{MM}	ESD Capability, Machine Model (Note 2)	200	V

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Refer to ELECTRICAL CHARACTERISTICS and APPLICATION INFORMATION for Safe Operating Area.
2. This device series incorporates ESD protection and is tested by the following methods:
   ESD Human Body Model tested per AEC−Q100−002.
   ESD Machine Model tested per AEC−Q100−003.
   Latch-up Current Maximum Rating ≤150 mA per AEC−Q100−004.

Table 3. THERMAL CHARACTERISTICS

Symbol	Rating	Value	Unit
	Thermal Characteristics, QFN20, 5x5, 0.65P package		
$R_{\theta JA}$	Thermal Resistance, Junction−to−Ambient (Note 5)	30.5	°C/W
$R_{\theta JC}$	Thermal Resistance, Junction−to−Case (bottom) (Note 6)	4.1	°C/W

3. Refer to ELECTRICAL CHARACTERISTICS and APPLICATION INFORMATION for Safe Operating Area.
4. Thermal data are derived by thermal simulations based on methodology specified in the JEDEC JESD51 series standards. The following assumptions are used in the simulations:
   − This data was generated with only a single device at the center of a high−K (2s2p) board with 3 in x 3 in copper area which follows the JEDEC51.7 guidelines.
   − The exposed pad is connected to the PCB ground layer through a 4x4 thermal via array. Vias are 0.3 mm diameter, plated.
   − Each of top and bottom copper layers has a dedicated pattern for 20% copper coverage.
5. The junction−to−ambient thermal resistance under natural convection is obtained in a simulation on a high−K board, following the JEDEC51.7 guidelines with assumptions as above, in an environment described in JESD51−2a.
6. The junction−to−case (bottom) thermal resistance is obtained by simulating a cold plate test on the IC exposed pad. Test description can be found in the ANSI SEMI standard G30−88.

Table 4. RECOMMENDED OPERATING CONDITIONS (Note 7)

Symbol	Rating	Min	Max	Unit
V_{IN}	Input Voltage	V_{OUT} + V_{DO}	5.5	V
V_{BIAS}	Bias Voltage	2.7	5.5	V
T_J	Junction Temperature	−40	125	°C

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

7. Refer to ELECTRICAL CHARACTERISTICS and APPLICATION INFORMATION for Safe Operating Area.

Share Feedback
Your Opinion Matters

Table 5. ELECTRICAL CHARACTERISTICS
(At V_{EN} = 1.1 V, V_{IN} = V_{OUT} + 0.3 V, C_{BIAS} = 0.1 μF, C_{SS} = 1 nF, C_{IN} = C_{OUT} = 10 μF, I_{OUT} = 50 mA, V_{BIAS} = 5.0 V, T_J = −40°C to +125°C, unless otherwise noted. Typical values are at T_J = +25°C.)

Symbol	Parameter	Test Conditions	Min	Typ	Max	Unit
V_{IN}	Input Voltage Range		V_{OUT} +V_{DO}		5.5	V
V_{BIAS}	Bias Pin Voltage Range		2.7		5.5	V
UVLO	Undervoltage Lock-out	V_{BIAS} rising Hysteresis	1.2	1.6 0.4	1.9	V
V_{REF}	Internal Reference (Adj.)	T_J = +25°C	0.798	0.802	0.806	V
V_{OUT}	Output Voltage Range	V_{IN} = 5 V, I_{OUT} = 3.0 A	V_{REF}		3.6	V
	Accuracy (Note 1)	V_{OUT} + 2.2 V < V_{BIAS} < 5.5 V, 50 mA < I_{OUT} < 3.0 A	- 2	±0.5	+ 2	%
V_{OUT}/V_{IN}	Line Regulation	$V_{OUT\ (NOM)}$ + 0.3 < V_{IN} < 5.5 V		0.03		%/V
V_{OUT}/I_{OUT}	Load Regulation	50mA < I_{OUT} < 3.0 A		0.09		%/A
V_{DO}	V_{IN} Dropout Voltage (Note 2)	I_{OUT} = 3.0 A, V_{BIAS} - $V_{OUT\ (NOM)}$ ≥ 3.25 V (Note 3)		120	280	mV
	V_{BIAS} Dropout Voltage (Note 2)	I_{OUT} = 3.0 A, V_{IN} = V_{BIAS}		1.31	1.75	V
I_{CL}	Current Limit	V_{OUT} = 80% x $V_{OUT\ (NOM)}$	3.5	4.6	7.0	A
I_{BIAS}	Bias Pin Current			1	2	mA
I_{SHDN}	Shutdown Supply Current (I_{GND})	V_{EN} ≤ 0.4 V		1	50	μA
I_{FB}	Feedback Pin Current		- 1	0.15	1	μA
PSRR	Power-supply Rejection (V_{IN} to V_{OUT})	1 kHz, I_{OUT} = 1.5 A, V_{IN} = 1.8 V, V_{OUT} = 1.5 V		60		dB
		300 kHz, I_{OUT} = 1.5 A, V_{IN} = 1.8 V, V_{OUT} = 1.5 V		30		
	Power-supply Rejection (V_{BIAS} to V_{OUT})	1 kHz, I_{OUT} = 1.5 A, V_{IN} = 1.8 V, V_{OUT} = 1.5 V		50		dB
		300 kHz, I_{OUT} = 1.5 A, V_{IN} = 1.8 V, V_{OUT} = 1.5 V		30		
Noise	Output Noise Voltage	100 Hz to 100 kHz, I_{OUT} = 3 A		25 x V_{OUT}		μV_{RMS}
t_{STRT}	Minimum Startup Time	R_{LOAD} for I_{OUT} = 1.0 A, C_{SS} = open		200		μs
I_{SS}	Soft-start Charging Current	V_{SS} = 0.4 V		0.44		μA
$V_{EN,\ HI}$	Enable Input High Level		1.1		5.5	V
$V_{EN,\ LO}$	Enable Input Low Level		0		0.4	V
$V_{EN,\ HYS}$	Enable Pin Hysteresis			50		mV
$V_{EN,\ DG}$	Enable Pin Deglitch Time			20		μs
I_{EN}	Enable Pin Current	V_{EN} = 5 V		0.1	1	μA
V_{IT}	PG Trip Threshold	V_{OUT} decreasing	85	90	94	$\%V_{OUT}$
V_{HYS}	PG Trip Hysteresis			3		$\%V_{OUT}$
$V_{PG,\ LO}$	PG Output Low Voltage	I_{PG} = 1 mA (Sinking), V_{OUT} < V_{IT}			0.3	V
$I_{PG,\ LKG}$	PG Leakage Current	V_{PG} = 5.25 V, V_{OUT} > V_{IT}		0.1	1	μA
TSD	Thermal Shutdown Temperature	Shutdown, temperature increasing Reset, temperature decreasing		+165 +140		°C

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.
1. Adjustable devices tested at V_{REF}; external resistor tolerance is not taken into account.
2. Dropout is defined as the voltage from the input to V_{OUT} when V_{OUT} is 3% below nominal.
3. 3.25 V is a test condition of this device and can be adjusted by referring to Figure 8.

Share Feedback
Your Opinion Matters

TYPICAL CHARACTERISTICS

AT T_J = +25°C, V_{IN} = $V_{OUT(TYP)}$ + 0.3 V, V_{BIAS} = 5 V, I_{OUT} = 50 MA, V_{EN} = V_{IN}, C_{IN} = 1 MF, C_{BIAS} = 4.7 MF, AND C_{OUT} = 10 MF, UNLESS OTHERWISE NOTED.



Figure 3. V_{IN} Line Regulation



Figure 4. V_{BIAS} Line Regulation



Figure 5. Load Regulation



Figure 6. Load Regulation



Figure 7. V_{IN} Dropout Voltage vs. I_{OUT} and Temperature T_J



Figure 8. V_{IN} Dropout Voltage vs. (V_{BIAS} − V_{OUT}) and Temperature T_J

Share Feedback
Your Opinion Matters

TYPICAL CHARACTERISTICS (continued)

AT T_J = +25°C, V_{IN} = $V_{OUT(TYP)}$ + 0.3 V, V_{BIAS} = 5 V, I_{OUT} = 50 MA, V_{EN} = V_{IN}, C_{IN} = 1 MF, C_{BIAS} = 4.7 MF, AND C_{OUT} = 10 MF, UNLESS OTHERWISE NOTED.



Figure 9. V_{IN} Dropout Voltage vs. (V_{BIAS} – V_{OUT}) and Temperature T_J



Figure 10. V_{BIAS} Dropout Voltage vs. I_{OUT} and Temperature T_J



Figure 11. BIAS Pin Current vs. I_{OUT} and Temperature T_J



Figure 12. BIAS Pin Current vs. V_{BIAS} and Temperature T_J



Figure 13. Soft Start Charging Current I_{SS} vs. Temperature T_J



Figure 14. L–level PG Voltage vs. Current

Share Feedback
Your Opinion Matters

TYPICAL CHARACTERISTICS (continued)

AT T_J = +25°C, V_{IN} = $V_{OUT(TYP)}$ + 0.3 V, V_{BIAS} = 5 V, I_{OUT} = 50 MA, V_{EN} = V_{IN}, C_{IN} = 1 MF, C_{BIAS} = 4.7 MF, AND C_{OUT} = 10 MF, UNLESS OTHERWISE NOTED.



Figure 15. Current Limit vs. (V_{BIAS} − V_{OUT})

Share Feedback
Your Opinion Matters

APPLICATIONS INFORMATION

The NCV59749 dual−rail very low dropout voltage regulator is using NMOS pass transistor for output voltage regulation from V_{IN} voltage. All the low current internal controll circuitry is powered from the V_{BIAS} voltage.

The use of an NMOS pass transistor offers several advantages in applications. Unlike a PMOS topology devices, the output capacitor has reduced impact on loop stability. Vin to Vout operating voltage difference can be very low compared with standard PMOS regulators in very low Vin applications.

The NCV59749 offers programmable smooth monotonic start-up. The controlled voltage rising limits the inrush current what is advantageous in applications with large capacitive loads. The Voltage Controlled Soft Start timing is programmable by external Css capacitor value.

The Enable (EN) input is equipped with internal hysteresis and deglitch filter.

Open Drain type Power Good (PG) output is available for Vout monitoring and sequencing of other devices.

NCV59749 is a Adjustable linear regulator. The required Output voltage can be adjusted by two external resistors. Typical application schematics is shown in Figure 16.



$$V_{OUT} = 0.8 \times \left(1 + R_1/R_2\right)$$

Figure 16. Typical Application Schematics

Dropout Voltage

Because of two power supply inputs V_{IN} and V_{BIAS} and one V_{OUT} regulator output, there are two Dropout voltages specified.

The first, the V_{IN} Dropout voltage is the voltage difference ($V_{IN} - V_{OUT}$) when V_{OUT} starts to decrease by percents specified in the Electrical Characteristics table. V_{BIAS} is high enough, specific value is published in the Electrical Characteristics table.

The second, V_{BIAS} dropout voltage is the voltage difference ($V_{BIAS} - V_{OUT}$) when V_{IN} and V_{BIAS} pins are joined together and V_{OUT} starts to decrease.

Input and Output Capacitors

The device is designed to be stable for all available types and values of output capacitors ≥ 2.2 μF. The device is also stable with multiple capacitors in parallel, which can be of any type or value.

In applications where no low input supplies impedance available (PCB inductance in V_{IN} and/or V_{BIAS} inputs as example), the recommended C_{IN} and C_{BIAS} value is 1 μF or greater. Ceramic or other low ESR capacitors are recommended**.** For the best performance all the capacitors should be connected to the NCV59749 respective pins directly in the device PCB copper layer, not through vias having not negligible impedance.

Enable Operation

The enable pin will turn the regulator on or off. The threshold limits are covered in the electrical characteristics table in this data sheet. If the enable function is not to be used then the pin should be connected to V_{IN} or V_{BIAS}.

Output Noise

When the NCV59749 device reaches the end of the Soft−Start cycle, the Soft Start capacitor is switched to serve as a Noise filtering capacitor.

Output Voltage Adjust

The output voltage can be adjusted from 0.8 V to 3.6 V using resistors divider between the output and the FB input. Recommended resistor values for frequently used voltages can be found in the Table 6.

Programmable Soft−Start

The Soft-Start ramp time depends on the Soft Start charging current I_{SS}, Soft-Start capacitor value C_{SS} and internal reference voltage V_{REF}.

The Soft –Start time can be calculated using following equations:

$t_{ss} = C_{SS} \times (V_{REF} / I_{SS})$ [s, F,V,A]

or in more practical units

$t_{SS} = C_{SS} \times 0.8V / 0.44 = C_{SS} \times 1.82$

where

t_{ss} = Soft−Start time in miliseconds

C_{SS} = Soft−Start capacitor value in nano Farads

Capacitor values for frequently used Soft-Start times can be found in the Table 7.

The maximal recommended value of C_{SS} capacitor is 15 nF. For higher C_{SS} values the capacitor full discharging before new Soft-Start cycle is not guaranteed.

Current Limitation

The internal Current Limitation circuitry allows the device to supply the full nominal current and surges but protects the device against Current Overload or Short.

Thermal Protection

Internal thermal shutdown (TSD) circuitry is provided to protect the integrated circuit in the event that the maximum junction temperature is exceeded. When TSD activated , the regulator output turns off. When cooling down under the low temperature threshold, device output is activated again. This TSD feature is provided to prevent failures from accidental overheating.

Share Feedback
Your Opinion Matters

Power Dissipation

The maximum power dissipation supported by the device is dependent upon board design and layout. Mounting pad configuration on the PCB, the board material, and the ambient temperature affect the rate of junction temperature rise for the part. For reliable operation junction temperature should be limited to +125°C.

Table 6. RESISTOR VALUES FOR PROGRAMMING THE OUTPUT VOLTAGE

V_{OUT} (V)	R_1 (kΩ)	R_2 (kΩ)
0.8	Short	Open
0.9	0.619	4.99
1.0	1.13	4.53
1.05	1.37	4.33
1.1	1.87	4.99
1.2	2.49	4.99
1.5	4.12	4.75
1.8	3.57	2.87
2.5	3.57	1.69
3.3	3.57	1.15

NOTE: $V_{OUT} = 0.8 \times (1 + R_1/R_2)$
Resistors in the table are standard 1% types

Table 7. CAPACITOR VALUES FOR PROGRAMMING THE SOFT−START TIME

Soft−Start Time	C_{SS}
0.2 ms	Open
0.5 ms	270 pF
1 ms	560 pF
5 ms	2.7 nF
10 ms	5.6 nF
18 ms	10 nF

Table 8. ORDERING INFORMATION

Device	Output Current	Output Voltage	Junction Temp. Range	Package	Shipping
NCV59749MNADJTBG	3.0 A	ADJ	−40°C to +125°C	QFN20 (Pb−Free)	3000 / Tape & Reel

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

Share Feedback
Your Opinion Matters

QFN20 5x5, 0.65P
CASE 485DB
ISSUE O

DATE 02 APR 2013



SCALE 2:1



TOP VIEW



DETAIL A
ALTERNATE TERMINAL CONSTRUCTIONS



DETAIL B
ALTERNATE CONSTRUCTION



SIDE VIEW



BOTTOM VIEW

NOTES:
1. DIMENSIONS AND TOLERANCING PER ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: MILLIMETERS.
3. DIMENSION b APPLIES TO PLATED TERMINAL AND IS MEASURED BETWEEN 0.25 AND 0.30 MM FROM THE TERMINAL TIP.
4. COPLANARITY APPLIES TO THE EXPOSED PAD AS WELL AS THE TERMINALS.
5. OPTIONAL FEATURES.

	MILLIMETERS	
DIM	MIN	MAX
A	0.80	1.00
A1	---	0.05
A3	0.20 REF	
b	0.25	0.35
D	5.00 BSC	
D2	3.05	3.25
E	5.00 BSC	
E2	3.05	3.25
e	0.65 BSC	
L	0.45	0.65
L1	---	0.15

GENERIC MARKING DIAGRAM*



XXXXX = Specific Device Code
A = Assembly Location
WL = Wafer Lot
YY = Year
WW = Work Week
▪ = Pb−Free Package

(Note: Microdot may be in either location)

*This information is generic. Please refer to device data sheet for actual part marking.
Pb−Free indicator, “G” or microdot “ ▪”, may or may not be present.

RECOMMENDED SOLDERING FOOTPRINT*



DIMENSIONS: MILLIMETERS

*For additional information on our Pb−Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

DOCUMENT NUMBER:	**98AON88183E**	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red.	
DESCRIPTION:	**QFN20 5x5, 0.65P**		**PAGE 1 OF 1**

onsemi and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2013

onsemi, , and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent−Marking.pdf. **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as−is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:
Technical Library: www.onsemi.com/design/resources/technical−documentation
onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support
For additional information, please contact your local Sales Representative at www.onsemi.com/support/sales

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.