Very Low Dropout Bias Rail CMOS Voltage Regulator, 500 mA

NCV8133

The NCV8133 is a 500 mA VLDO equipped with NMOS pass transistor and a separate bias supply voltage (V_{BIAS}). The device provides very stable, accurate output voltage with low noise suitable for space constrained, noise sensitive applications. In order to optimize performance for battery operated portable applications, the NCV8133 features low I_Q consumption. The XDFN6 1.2 mm x 1.2 mm package is optimized for use in space constrained applications.

Features

- Input Voltage Range: 0.8 V to 5.5 V
- Bias Voltage Range: 2.4 V to 5.5 V
- Fixed Output Voltage Device
- Output Voltage Range: 0.8 V to 2.1 V
- ±1.5% Accuracy over Temperature, 0.5% V_{OUT} @ 25°C
- Ultra−Low Dropout: Typ. 140 mV at 500 mA
- Very Low Bias Input Current of Typ. 80 μA
- Very Low Bias Input Current in Disable Mode: Typ. 0.5 μA
- Logic Level Enable Input for ON/OFF Control
- Output Active Discharge Option Available
- Stable with a 2.2 μF Ceramic Capacitor
- NCV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC−Q100 Qualified and PPAP Capable; Device Temperature Grade 1: −40°C to +125°C Ambient Operating Temperature Range
- These are Pb−Free Devices

Typical Applications

- Automotive, Consumer and Industrial Equipment Point of Load Regulation
- Battery−powered Equipment
- FPGA, DSP and Logic Power Supplies
- Switching Power Supply Post Regulation
- Cameras, DVRs, STB and Camcorders



Figure 1. Typical Application Schematics



XDFN6
CASE 711AT

MARKING DIAGRAM



XX = Specific Device Code
M = Date Code

PIN CONNECTIONS



(Top View)

ORDERING INFORMATION

See detailed ordering and shipping information on page 10 of this data sheet.

© Semiconductor Components Industries, LLC, 2017



*Active output discharge function is present only in NCV8133AMXyyyTCG devices.
yyy denotes the particular output voltage option.

Figure 2. Simplified Schematic Block Diagram

PIN FUNCTION DESCRIPTION

Pin No. XDFN6	Pin Name	Description
1	OUT	Regulated Output Voltage pin
2	N/C	Not internally connected (Note 1)
3	EN	Enable pin. Driving this pin high enables the regulator. Driving this pin low puts the regulator into shutdown mode.
4	BIAS	Bias voltage supply for internal control circuits. This pin is monitored by internal Under-Voltage Lockout Circuit.
5	GND	Ground
6	IN	Input Voltage Supply pin
Pad		Should be soldered to the ground plane for increased thermal performance.

1. True no connect. Printed circuit board traces are allowable

ABSOLUTE MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Input Voltage (Note 2)	V_{IN}	−0.3 to 6	V
Output Voltage	V_{OUT}	−0.3 to (V_{IN}+0.3) ≤ 6	V
Chip Enable, Bias and Adj Input	V_{EN}, V_{BIAS}	−0.3 to 6	V
Output Short Circuit Duration	t_{SC}	unlimited	s
Maximum Junction Temperature	T_J	150	°C
Storage Temperature	T_{STG}	−55 to 150	°C
ESD Capability, Human Body Model (Note 3)	ESD_{HBM}	2000	V
ESD Capability, Machine Model (Note 3)	ESD_{MM}	200	V

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

2. Refer to ELECTRICAL CHARACTERISTICS and APPLICATION INFORMATION for Safe Operating Area.
3. This device series incorporates ESD protection (except OUT pin) and is tested by the following methods:
   ESD Human Body Model tested per AEC−Q100−002
   ESD Machine Model tested per AEC−Q100−003
   Latchup Current Maximum Rating ≤ 150 mA per AEC−Q100−004.

RECOMMENDED OPERATING CONDITIONS

Rating	Symbol	Min	Max	Unit
Input Voltage	V_{IN}	(V_{OUT} + V_{DO_IN})	5.5	V
Bias Voltage	V_{BIAS}	(V_{OUT} + 1.4) ≥ 2.4	5.5	V
Junction Temperature	T_J	−40	+125	°C

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

THERMAL CHARACTERISTICS

Rating	Symbol	Value	Unit
Thermal Characteristics, XDFN6 1.2 mm x 1.2 mm Thermal Resistance, Junction−to−Air	$R_{\theta JA}$	170	°C/W

ELECTRICAL CHARACTERISTICS $-40°C \le T_J \le 125°C$; V_{BIAS} = 2.7 V or (V_{OUT} + 1.6 V), whichever is greater, $V_{IN} = V_{OUT(NOM)}$ + 0.3 V, I_{OUT} = 1 mA, V_{EN} = 1 V, unless otherwise noted. C_{IN} = 1 μF, C_{OUT} = 2.2 μF. Typical values are at T_J = +25°C. Min/Max values are for $-40°C \le T_J \le 125°C$ unless otherwise noted. (Note 4)

Parameter	Test Conditions	Symbol	Min	Typ	Max	Unit
Operating Input Voltage Range		V_{IN}	V_{OUT} + V_{DO}		5.5	V
Operating Bias Voltage Range		V_{BIAS}	(V_{OUT} + 1.40) ≥ 2.4		5.5	V
Undervoltage Lock−out	V_{BIAS} Rising Hysteresis	UVLO		1.6 0.2		V
Output Voltage Accuracy		V_{OUT}		±0.5		%
Output Voltage Accuracy	$-40°C \le T_J \le 125°C$, $V_{OUT(NOM)}$ + 0.3 V ≤ V_{IN} ≤ $V_{OUT(NOM)}$ + 1.0 V, 2.7 V or ($V_{OUT(NOM)}$ + 1.6 V), whichever is greater < V_{BIAS} < 5.5 V, 1 mA < I_{OUT} < 500 mA	V_{OUT}	−1.5		+1.5	%
V_{IN} Line Regulation	$V_{OUT(NOM)}$ + 0.3 V ≤ V_{IN} ≤ 5.0 V	$Line_{Reg}$		0.01		%/V
V_{BIAS} Line Regulation	2.7 V or ($V_{OUT(NOM)}$ + 1.6 V), whichever is greater < V_{BIAS} < 5.5 V	$Line_{Reg}$		0.01		%/V
Load Regulation	I_{OUT} = 1 mA to 500 mA	$Load_{Reg}$		1.5		mV
V_{IN} Dropout Voltage	I_{OUT} = 150 mA (Note 5)	V_{DO}		37	90	mV
	I_{OUT} = 500 mA (Note 5)	V_{DO}		140	300	
V_{BIAS} Dropout Voltage	I_{OUT} = 500 mA, $V_{IN} = V_{BIAS}$ (Notes 5, 6)	V_{DO}		1.1	1.5	V
Output Current Limit	V_{OUT} = 90% $V_{OUT(NOM)}$	I_{CL}	550	800	1100	mA
Bias Pin Operating Current	V_{BIAS} = 2.7 V	I_{BIAS}		80	110	μA
Bias Pin Disable Current	$V_{EN} \le 0.4$ V	$I_{BIAS(DIS)}$		0.5	1.5	μA
Vinput Pin Disable Current	$V_{EN} \le 0.4$ V	$I_{VIN(DIS)}$		0.5	1.5	μA
EN Pin Threshold Voltage	EN Input Voltage “H”	$V_{EN(H)}$	0.9			V
	EN Input Voltage “L”	$V_{EN(L)}$			0.4	
EN Pull Down Current	V_{EN} = 5.5 V	I_{EN}		0.3	1.5	μA
Turn−On Time	From assertion of V_{EN} to V_{OUT} = 98% $V_{OUT(NOM)}$. $V_{OUT(NOM)}$ = 1.0 V	t_{ON}		150		μs
Power Supply Rejection Ratio	V_{IN} to V_{OUT}, f = 1 kHz, I_{OUT} = 150 mA, $V_{IN} \ge V_{OUT}$ +0.5 V	PSRR(V_{IN})		70		dB
	V_{BIAS} to V_{OUT}, f = 1 kHz, I_{OUT} = 150 mA, $V_{IN} \ge V_{OUT}$ +0.5 V	PSRR(V_{BIAS})		80		dB
Output Noise Voltage	$V_{IN} = V_{OUT}$ +0.5 V, $V_{OUT(NOM)}$ = 1.0 V, f = 10 Hz to 100 kHz	V_N		40		μV_{RMS}
Thermal Shutdown Threshold	Temperature increasing			160		°C
	Temperature decreasing			140		
Output Discharge Pull−Down	$V_{EN} \le 0.4$ V, V_{OUT} = 0.5 V, NCV8133A options only	R_{DISCH}		150		Ω

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

4. Performance guaranteed over the indicated operating temperature range by design and/or characterization. Production tested at T_A = 25°C. Low duty cycle pulse techniques are used during the testing to maintain the junction temperature as close to ambient as possible.
5. Dropout voltage is characterized when V_{OUT} falls 3% below $V_{OUT(NOM)}$.
6. For output voltages below 0.9 V, V_{BIAS} dropout voltage does not apply due to a minimum Bias operating voltage of 2.4 V.

TYPICAL CHARACTERISTICS

At T_J = +25°C, V_{IN} = $V_{OUT(TYP)}$ + 0.3 V, V_{BIAS} = 2.7 V, V_{EN} = V_{BIAS}, $V_{OUT(NOM)}$ = 1.0 V, I_{OUT} = 500 mA, C_{IN} = 1 μF, C_{BIAS} = 0.1 μF, and C_{OUT} = 2.2 μF (effective capacitance), unless otherwise noted.



Figure 3. V_{IN} Dropout Voltage vs. I_{OUT} and Temperature T_J



Figure 4. V_{IN} Dropout Voltage vs. (V_{BIAS} – V_{OUT}) and Temperature T_J



Figure 5. V_{IN} Dropout Voltage vs. (V_{BIAS} – V_{OUT}) and Temperature T_J



Figure 6. V_{IN} Dropout Voltage vs. (V_{BIAS} – V_{OUT}) and Temperature T_J



Figure 7. V_{BIAS} Dropout Voltage vs. I_{OUT} and Temperature T_J



Figure 8. BIAS Pin Current vs. I_{OUT} and Temperature T_J

TYPICAL CHARACTERISTICS

At T_J = +25°C, V_{IN} = $V_{OUT(TYP)}$ + 0.3 V, V_{BIAS} = 2.7 V, V_{EN} = V_{BIAS}, $V_{OUT(NOM)}$ = 1.0 V, I_{OUT} = 500 mA, C_{IN} = 1 μF, C_{BIAS} = 0.1 μF, and C_{OUT} = 2.2 μF (effective capacitance), unless otherwise noted.



Figure 9. BIAS Pin Current vs. V_{BIAS} and Temperature T_J



Figure 10. Current Limit vs. (V_{BIAS} − V_{OUT})

TYPICAL CHARACTERISTICS

At T_J = +25°C, V_{IN} = $V_{OUT(TYP)}$ + 0.3 V, V_{BIAS} = 2.7 V, V_{EN} = V_{BIAS}, $V_{OUT(NOM)}$ = 1.0 V, I_{OUT} = 500 mA, C_{IN} = 1 μF, C_{BIAS} = 0.1 μF, and C_{OUT} = 2.2 μF (effective capacitance), unless otherwise noted.



Figure 11. Load Transient Response, I_{OUT} = 50 mA to 500 mA, C_{OUT} = 10 μF



Figure 12. Load Transient Response, I_{OUT} = 50 mA to 500 mA, C_{OUT} = 2.2 μF



Figure 13. Load Transient Response, I_{OUT} = 1 mA to 500 mA, C_{OUT} = 10 μF



Figure 14. Load Transient Response, I_{OUT} = 1 mA to 500 mA, C_{OUT} = 2.2 μF



Figure 15. Enable Turn−on Response, Output Resistive Load 500 mA, C_{OUT} = 10 μF



Figure 16. Enable Turn−on Response, I_{OUT} = 0 mA, C_{OUT} = 2.2 μF

TYPICAL CHARACTERISTICS

At T_J = +25°C, V_{IN} = $V_{OUT(TYP)}$ + 0.3 V, V_{BIAS} = 2.7 V, V_{EN} = V_{BIAS}, $V_{OUT(NOM)}$ = 1.0 V, I_{OUT} = 500 mA, C_{IN} = 1 μF, C_{BIAS} = 0.1 μF, and C_{OUT} = 2.2 μF (effective capacitance), unless otherwise noted.



Figure 17. V_{IN} Line Transient Response, V_{IN} = 1.3 V to 2.3 V, I_{OUT} = 100 mA, C_{OUT} = 10 μF



Figure 18. V_{IN} Line Transient Response, V_{IN} = 1.3 V to 2.3 V, I_{OUT} = 100 mA, C_{OUT} = 2.2 μF

APPLICATIONS INFORMATION



Figure 19. Typical Application: Low−Voltage DC/DC Post−Regulator with ON/OFF Functionality

The NCV8133 dual−rail very low dropout voltage regulator is using NMOS pass transistor for output voltage regulation from V_{IN} voltage. All the low current internal control circuitry is powered from the V_{BIAS} voltage.

The use of an NMOS pass transistor offers several advantages in applications. Unlike PMOS topology devices, the output capacitor has reduced impact on loop stability. Vin to Vout operating voltage difference can be very low compared with standard PMOS regulators in very low Vin applications.

The NCV8133 offers smooth monotonic start-up. The controlled voltage rising limits the inrush current.

The Enable (EN) input is equipped with internal hysteresis.

NCV8133 is a Fixed Voltage linear regulator.

Dropout Voltage

Because of two power supply inputs V_{IN} and V_{BIAS} and one V_{OUT} regulator output, there are two Dropout voltages specified.

The first, the V_{IN} Dropout voltage is the voltage difference ($V_{IN} - V_{OUT}$) when V_{OUT} starts to decrease by percent specified in the Electrical Characteristics table. V_{BIAS} is high enough; specific value is published in the Electrical Characteristics table.

The second, V_{BIAS} dropout voltage is the voltage difference ($V_{BIAS} - V_{OUT}$) when V_{IN} and V_{BIAS} pins are joined together and V_{OUT} starts to decrease.

Input and Output Capacitors

The device is designed to be stable for ceramic output capacitors with Effective capacitance in the range from 2.2 μF to 10 μF. The device is also stable with multiple capacitors in parallel, having the total effective capacitance in the specified range.

In applications where no low input supplies impedance available (PCB inductance in V_{IN} and/or V_{BIAS} inputs as example), the recommended C_{IN} = 1 μF and C_{BIAS} = 0.1 μF or greater. Ceramic capacitors are recommended**.** For the best performance all the capacitors should be connected to the NCV8133 respective pins directly in the device PCB copper layer, not through vias having not negligible impedance.

When using small ceramic capacitor, their capacitance is not constant but varies with applied DC biasing voltage, temperature and tolerance. The effective capacitance can be much lower than their nominal capacitance value, most importantly in negative temperatures and higher LDO output voltages. That is why the recommended Output capacitor capacitance value is specified as Effective value in the specific application conditions.

Enable Operation

The enable pin will turn the regulator on or off. The threshold limits are covered in the electrical characteristics table in this data sheet. If the enable function is not to be used then the pin should be connected to V_{IN} or V_{BIAS}.

Current Limitation

The internal Current Limitation circuitry allows the device to supply the full nominal current and surges but protects the device against Current Overload or Short.

Thermal Protection

Internal thermal shutdown (TSD) circuitry is provided to protect the integrated circuit in the event that the maximum junction temperature is exceeded. When TSD activated , the regulator output turns off. When cooling down under the low temperature threshold, device output is activated again. This TSD feature is provided to prevent failures from accidental overheating.

Power Dissipation

The maximum power dissipation supported by the device is dependent upon board design and layout. Mounting pad configuration on the PCB, the board material, and the ambient temperature affect the rate of junction temperature rise for the part. For reliable operation, junction temperature should be limited to +125°C.

ORDERING INFORMATION

Device	Nominal Output Voltage	Marking	Option	Package	Shipping†
NCV8133BMX080TCG	0.80 V	JL	Non−Active Discharge	XDFN6 (Pb−Free)	3000 or 5000 / Tape & Reel (Note 7)
NCV8133BMX100TCG (Note 7)	1.00 V	JM			
NCV8133BMX110TCG (Note 7)	1.10 V	JD			
NCV8133BMX120TCG (Note 7)	1.20 V	JE			
NCV8133BMX130TCG (Note 7)	1.30 V	JN			
NCV8133BMX150TCG (Note 7)	1.50 V	JF			
NCV8133BMX180TCG	1.80 V	JG			

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

To order other package and voltage variants, please contact your **onsemi** sales representative.

7. Products processed after October 1, 2022 are shipped with quantity 5000 units / tape & reel.

SCALE 4:1

XDFN6 1.20x1.20, 0.40P
CASE 711AT
ISSUE C

DATE 04 DEC 2015



TOP VIEW



SIDE VIEW



BOTTOM VIEW



DETAIL A
OPTIONAL
CONSTRUCTION

NOTES:
1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: MILLIMETERS.
3. DIMENSION b APPLIES TO THE PLATED TERMINALS.
4. COPLANARITY APPLIES TO THE PAD AS WELL AS THE TERMINALS.

	MILLIMETERS		
DIM	MIN	TYP	MAX
A	0.30	0.37	0.45
A1	0.00	0.03	0.05
b	0.13	0.18	0.23
D	1.15	1.20	1.25
D2	0.84	0.94	1.04
E	1.15	1.20	1.25
E2	0.20	0.30	0.40
e	0.40 BSC		
L	0.15	0.20	0.25
L1	0.00	0.05	0.10

GENERIC MARKING DIAGRAM*



XX = Specific Device Code
M = Date Code

*This information is generic. Please refer to device data sheet for actual part marking. Pb−Free indicator, “G” or microdot “ ▪”, may or may not be present.

RECOMMENDED MOUNTING FOOTPRINT*



DIMENSIONS: MILLIMETERS

*For additional information on our Pb−Free strategy and soldering details, please download the **onsemi** Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

DOCUMENT NUMBER:	**98AON76141F**	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red.	
DESCRIPTION:	**XDFN6, 1.20 X 1.20, 0.40P**		**PAGE 1 OF 1**

onsemi and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2013

onsemi, , and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent−Marking.pdf. **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as−is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:
Technical Library: www.onsemi.com/design/resources/technical−documentation
onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support
For additional information, please contact your local Sales Representative at www.onsemi.com/support/sales

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.